

MEDIA PLAYER AMPLIFIERS

MPA Media Player Amplifiers

Media amplifiers with integrated music player.

MPA60

MPA60 – D class mixing media amplifier powered by switching power supply. Integrated USB, SD card player/recorder, FM radio and Bluetooth player interface with IR remote control. Low and high impedance outputs, priority input, phantom power and tone control. Audio recording function is performed on memory cards or USB Flash drive. For precise input gain settings all rear panel inputs have gain adjusting potentiometers. No cooling FAN inside. User-friendly control, no need for professional installation assistance. The MPA 60 supports compressed audio files and is an excellent device for small size applications where amplification with music source or audio signal mixing is required.



Technical Specifications	MPA 60
Output power	60W
Power supply	110~230V, 50/60Hz
Outputs	Low impedance output - 4Ω, 8Ω Hi impedance outputs 70V, 100V
Inputs	MIC: Sensitivity: -6dB ~ -50dB Priority Input - CH1 Connectors: - XLR for CH1, Balanced TRS 6.3 jack for CH2 and CH3 LINE: Sensitivity: +14 ~ -30dBu Connector: RCA, 3,5mm TRS jack TELE PAGING: Sensitivity: 0 ~ -30dBu Connector: Phoenix
Frequency response	80 Hz -18 kHz
Tone control	Bass 100Hz ±12 dB, Treble 10kHz ±12dB
THD	< 0,5%
Indicators	Power, audio signal, clip, protect.
Controls	MIC and LINE input level controls, tone control, USB SD card player volume control, master volume control.
Phantom power	14V
Dimensions	260 mm x 270 mm x 90 mm
Weight	3,5 kg